

# EP Cores (6595100121)



Part Number: 6595100121

95 EP CORE SET

**EP designs reduce the effect of residual air gap upon the effective permeability of the core, hence they minimize coil volume for a given inductance. EP cores also provide a high degree of isolation from adjacent components and are advantageously used in low power devices, matching and broadband transformers.**

□ EP cores can be supplied with the center post gapped to a mechanical dimension or an  $A_L$  value.

Weight indicates is per pair or set.

Weight: 1.4 (g)

Dim	mm	mm tol	nominal inch	inch misc.
A	11.5	± 0.30	0.453	<input type="checkbox"/>
B	5.1	± 0.20	0.201	<input type="checkbox"/>
C	7.7	± 0.20	0.303	<input type="checkbox"/>
D	3.8	± 0.20	0.15	<input type="checkbox"/>
E	9.4	± 0.20	0.37	<input type="checkbox"/>
F	3.3	± 0.20	0.13	<input type="checkbox"/>
K	1.95	min	0.077	<input type="checkbox"/>

### Chart Legend

$\Sigma l / A$  : Core Constant,  $l_e$  : Effective Path Length,  
 $A_e$  : Effective Cross- Sectional Area,  $V_e$  : Effective Core Volume  
 $A_L$  : Inductance Factor

Explanation of Part Numbers: Digits 1 & 2 = product class and 3 & 4 = material grade.

Electrical Properties	
$A_L$ (nH)	1200 ±25%
$A_e$ (cm <sup>2</sup> )	0.11
$\Sigma l / A$ (cm <sup>-1</sup> )	16.8
$l_e$ (cm)	1.85
$V_e$ (cm <sup>3</sup> )	0.203
$A_{min}$ (cm <sup>2</sup> )	0.085

$A_L$  value is measured at 1 kHz, B < 10 gauss